

Overview

Aruba 7000 Series Mobility Controllers

Improved network performance, visibility, and control

Aruba 7000 Series Mobility Controllers enhance WLAN performance by centralizing all control functionality for individual Aruba access points (APs) to improve AP utilization, security, and client roaming. Ideally suited for midsize campuses and branches, the 7000 Series can be deployed using Zero Touch Provisioning (ZTP) to simplify deployment.



Aruba 7000 Series Mobility Controllers

Key Features

- 7005 Mobility Controller is a compact, fanless entry-level branch platform that can be powered by a Power-over-Ethernet (PoE) switch.
- 7008 Mobility Controller is a compact, fanless entry-level branch platform with 8 integrated PoE and PoE+ switch ports for small branch locations with some PoE requirements
- 7010 Mobility Controller is designed for mid-sized branch deployments that require several PoE and PoE+ switch ports.
- 7024 Mobility Controller is designed for mid-sized branch offices that require up to 24 switch ports for unified wired and wireless access.
- 7030 Mobility Controller is ideal for mid- to large- sized branch deployments that require unprecedented scale and performance.

Standard Features

Simple and Secure Access

The 7000 Series serves a key role in Dynamic Segmentation, providing Aruba's Policy Enforcement Firewall (PEF) to enforce policies based on user role, device type, application, and network location - and simplifying and securing wired and wireless network access. Traffic is encapsulated in GRE tunnels for complete encryption all the way from an AP or switch. This feature can be enabled with the ArubaOS PEF license and eliminates the need to manually configure SSIDs, VLANs or ACLs for each new client on the network.

High Performance and Reliability

Each 7000 Series provides connectivity for up to 4,096 concurrent users or client devices, 64 access points and include up to 24 Ethernet ports and multiple WAN uplinks. With 8Gbps of maximum throughput to perform Policy Enforcement Firewall (PEF) features, the 7000 Series delivers plenty of horsepower for the most demanding enterprise environments. These capabilities are over 40 times the client density and 10 times the maximum throughput of typical network appliances. For enhanced resiliency and availability, the 7000 Series can be clustered together in a network.

24/7 Mission-critical Networking

Aruba's unique patented wireless technologies are based on AI-powered machine learning algorithms and integrated directly into ArubaOS. Adaptive Radio Management, AirMatch and ClientMatch (now enhanced with Wi-Fi 6 grouping) provide RF optimization techniques to improve user experience and network health based on changing environmental conditions, correct for noisy or congested RF and resolve sticky client issues during user roaming. RFProtect provides advanced spectrum analysis and wireless intrusion protection (WIPS/WIDS) to help identify and mitigate Wi-Fi and non-Wi-Fi sources of interference, as well as containment of potential security risks. Learn more about Aruba's software features on the ArubaOS datasheet.

When deployed with Aruba Mobility Master, the 7000 Series can be joined to a controller cluster to increase scale, improve reliability using High Availability (HA), adopt configurations seamlessly based on hierarchy, support Live Upgrades to reduce maintenance windows, and share licenses from a global licensing pool. The 7000 Series also serves a key policy enforcement role in Aruba's 360 Secure Fabric. Aruba AirWave provides real-time monitoring, reporting and Wi-Fi planning and visibility services.

Microsoft Features

Aruba's integration with Microsoft enables unique application intelligence that detects Microsoft 365, Teams and Skype for Business traffic and then prioritizes them over less critical applications. Through management interfaces on ArubaOS, Aruba Central, and Aruba AirWave, IT can visualize call quality metrics such as MOS, latency, jitter, and packet loss for additional insights.

Mobility Controller Deployment

The Aruba 7000 Series can be deployed using Aruba Mobility Controller software licenses in a campus or branch access layer deployment. In this mode, the controllers cannot be simultaneously used for SD-WAN. In Mobility Controller mode, the 7000 Series can also participate in Aruba's Dynamic Segmentation framework, with, at minimum, an access point (AP) license and a Policy Enforcement Firewall (PEF) license for each Aruba access point and switch in the network.

SD-WAN Deployment

Refer to the SD-WAN use cases guide for more information on how the 7000 Series can be used. Each 7000 Series requires an Aruba Central software subscription license to enable SD-WAN software features and the use of cloud-based management. The SD-WAN license also enables the use of the entire bandwidth capacity stated in the data sheet for each gateway.

- For micro-branch deployments, the 7005, 7008 (and 9004) can be ordered with a base capacity license that supports up to 75 client devices each.
- In high availability deployments, each primary and backup appliances need to have a separate subscription license applied.

Each SD-WAN Base Capacity subscription includes software support and TAC/phone support. For SD-WAN hardware replacement support, order hardware-only support SKUs through your Aruba value-added reseller (VAR).

Service and Warranty Information

- Hardware: 1 year parts/ labor, can be extended with support contract
 - Software: 90 days, can be extended with support contract
-



Standard Features

Enhanced Capabilities

- **Wi-Fi 6 (802.11ax) enhanced with ClientMatch**

The latest Wi-Fi standard brings enhanced performance, speed, and efficiency with key features such as OFDMA, 1024-QAM, and bidirectional MU-MIMO. Combined with Aruba's patented ClientMatch technology, 802.11ax clients will now be grouped together to optimize the multi-user experience.

- **Enhanced wireless security**

Support for WPA3 brings stronger encryption and authentication methods, while Enhanced Open brings automatic security to open networks. New WPA2-MPSK feature enables simpler passkey management for WPA2 devices – should the Wi-Fi password on one device need to be changed, no additional key changes are needed for other devices on the network.

- **Dynamic Segmentation**

To simplify and better secure wired and wireless network access, the 7000 Series can enforce per-user and device roles across wired and wireless networks by integrating with ClearPass Policy Manager. This ensures consistent policy regardless of user role and device type, and eliminates the need to configure unnecessary SSIDs, ACLs, VLANs and subnets at every node in the network.

- **Policy Enforcement Firewall**

Enabled by the PEF license, wired and wireless user and application traffic can be tunneled to a stateful firewall on the 7000 Series through GRE tunnels for inspection. Policies are then enforced based on user role, device type, application and location - as described in Dynamic Segmentation.

- **Application visibility and control**

As part of the PEF license, application visibility with Deep Packet Inspection (DPI) technology evaluates and optimizes performance and Quality of Service policies for over 3,000 applications - even for encrypted or hidden traffic.

- **Web content filtering**

WebCC is an add-on subscription-based feature that classifies websites by content category and rates them by reputation. It can also block, apply QoS, bandwidth-limit, mirror, and log web content.

- **Unified Communications and Collaboration (UCC)**

Visualize and troubleshoot networks based on call quality metrics such as MOS, latency, jitter and packet loss. Supported applications include: Teams, Skype for Business[®], Wi-Fi Calling, Facetime, SIP, Jabber, Spark and more.

- **Zero Touch Provisioning**

The 7000 Series can be factory-shipped and deployed onsite with cloud-based Aruba Activate. For network-specific requirements, settings can be applied based on hierarchical configuration.

- **Integrated VPN services**

With support for IPSec/SSL VPNs, Aruba remote APs (RAPs) and Aruba VIA VPN users can establish encrypted sessions without any additional hardware required.

- **Third-party security integration**

For advanced malware or antivirus protection, the 7000 Series can assume the role of an on-premises agent of centrally-hosted firewalls such as those provided by Palo Alto Networks and Check Point Software. Dedicated firewall appliances are no longer needed at each branch.



Configuration Information

7000 Ordering Guide

Remarks	Description	SKU
	Step 1: Select the appropriate 7005 Chassis	
	Aruba 7005 (RW) 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW633A
	Aruba 7005 (US) 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW634A
	Aruba 7005 (IL) 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW637A
	Aruba 7005 (JP) 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW639A
	Aruba 7005 (EG) 4x 10/100/1000BASE-T Ports 16 AP Branch Controller	JY849A
	Aruba 7005 (RW) FIPS/TAA-compliant 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW635A
	Aruba 7005 (US) FIPS/TAA-compliant 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW636A
	Aruba 7005 (IL) FIPS/TAA-compliant 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW638A
	Aruba 7005 (JP) FIPS/TAA-compliant 4-port 10/100/1000BASE-T 16 AP and 1K Client Controller	JW640A
	Step 2: Select Power Supply (Optional)	
	AP-AC2-12A 12V/48W AC/DC desktop style power adapter with 1.7/4.0mm connector	R3J99A
Notes:	7005 Controller is normally powered by 802.3at compliant PoE	
	Step 3: Power Cord for Optional Supply (JX989A)	
	PC-AC-ARG AC power cord 250V/10A 1.8m C13 to IRAM 2073	JW113A
	PC-AC-AUS AC power cord 250V/10A 1.8m C13 to AS3112	JW114A
	PC-AC-BR AC power cord 250V/10A 1.8m C13 to NBR 14136	JW115A
	PC-AC-CHN AC power cord 250V/10A 1.8m C13 to GB2099	JW116A
	PC-AC-DEN AC power cord 250V/10A 1.8m C13 to AFSNIT 107-2-D1	JW117A
	PC-AC-EC AC power cord 250V/10A 1.8m C13 to CEE7/7	JW118A
	PC-AC-IN AC power cord 250V/6A 1.8m C13 to IS1293	JW119A
	PC-AC-IL AC power cord 250V/10A 1.8m C13 to SI32	JW120A
	PC-AC-IT AC power cord 250V/10A 1.8m C13 to CEI 23-50	JW121A
	PC-AC-JPN AC power cord 125V/12A 1.8m C13 to JISC 8303	JW122A
	PC-AC-KOR AC power cord 250V/7A 1.8m C13 to KSC 8305	JW123A
	PC-AC-NA AC power cord 125V/10A 1.8m C13 to NEMA 5-15P	JW124A
	PC-AC-SWI AC power cord 220V/10A 1.8m C13 to SEV 1011	JW125A
	PC-AC-UK AC power cord 250V/10A 1.8m C13 to BS1363	JW127A
	PC-AC-ZA AC power cord 250V/10A 1.8m C13 to SANS 164-1	JW128A
	Step 4: Shelf Mount Kit (Optional)	
	Aruba 7005-MNT-19 7005 Series 19-inch Rack Mount Kit	JW084A



Configuration Information

7008 Ordering Guide

Remarks	Description	SKU
	Step 1: Select the appropriate 7008 Chassis	
	Aruba 7008 (IL) 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX925A
	Aruba 7008 (JP) 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX926A
	Aruba 7008 (RW) 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX927A
	Aruba 7008 (US) 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX928A
	Aruba 7008 (IL) FIPS/TAA 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX929A
	Aruba 7008 (JP) FIPS/TAA 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX930A
	Aruba 7008 (RW) FIPS/TAA 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX931A
	Aruba 7008 (US) FIPS/TAA 8p 100W PoE+ 10/100/1000BASE-T 16 AP and 1K Client Controller	JX932A
	Step 2: Select AC power cord for main power supply	
	PC-AC-ARG AC power cord 250V/10A 1.8m C13 to IRAM 2073	JW113A
	PC-AC-AUS AC power cord 250V/10A 1.8m C13 to AS3112	JW114A
	PC-AC-BR AC power cord 250V/10A 1.8m C13 to NBR 14136	JW115A
	PC-AC-CHN AC power cord 250V/10A 1.8m C13 to GB2099	JW116A
	PC-AC-DEN AC power cord 250V/10A 1.8m C13 to AFSNIT 107-2-D1	JW117A
	PC-AC-EC AC power cord 250V/10A 1.8m C13 to CEE7/7	JW118A
	PC-AC-IN AC power cord 250V/6A 1.8m C13 to IS1293	JW119A
	PC-AC-IL AC power cord 250V/10A 1.8m C13 to SI32	JW120A
	PC-AC-IT AC power cord 250V/10A 1.8m C13 to CEI 23-50	JW121A
	PC-AC-JPN AC power cord 125V/12A 1.8m C13 to JISC 8303	JW122A
	PC-AC-KOR AC power cord 250V/7A 1.8m C13 to KSC 8305	JW123A
	PC-AC-NA AC power cord 125V/10A 1.8m C13 to NEMA 5-15P	JW124A
	PC-AC-SWI AC power cord 220V/10A 1.8m C13 to SEV 1011	JW125A
	PC-AC-UK AC power cord 250V/10A 1.8m C13 to BS1363	JW127A
	PC-AC-ZA AC power cord 250V/10A 1.8m C13 to SANS 164-1	JW128A
	Step 3: Shelf Mount Kit (Optional)	
	Aruba 7008-MNT-19 7008 Series 19-inch Rack Mount Kit	JX934A



Configuration Information

7010 Ordering Guide

Remarks	Description	SKU
	Step 1: Select the appropriate 7010 Chassis	
	Aruba 7010 (RW) 16p 150W PoE+ 10/100/1000BASE-T 1G BASE-X SFP 32 AP and 2K Clients Controller	JW678A
	Aruba 7010 (US) 16p 150W PoE+ 10/100/1000BASE-T 1G BASE-X SFP 32 AP and 2K Clients Controller	JW679A
	Aruba 7010(IL) 16p 150W PoE+ 10/100/1000BASE-T 1G BASE-X SFP 32 for AP and 2K Clients Cntrlr	JW680A
	Aruba 7010 (JP) 16p 150W PoE+ 10/100/1000BASE-T 1G BASE-X SFP for 32 AP and 2K Clients Cntrlr	JW681A
	Aruba 7010 (EG) 16x 1000BASE-T + 2x SFP Ports 32 AP Branch Controller	JY850A
	Aruba 7010 (RW) FIPS/TAA 16p 150W PoE+ 10/100/1000BASE-T 1GBASE-X SFP 32 AP and 2K Clnts Cntrlr	JW702A
	Aruba 7010 (US) FIPS/TAA 16p 150W PoE+ 10/100/1000BASE-T 1GBASE-X SFP 32 AP and 2K Clnts Cntrlr	JW703A
	Aruba 7010 (IL) FIPS/TAA 16p 150W PoE+ 10/100/1000BASE-T 1G BASE-X SFP 32 AP and 2K Clnts Cntrlr	JW704A
	Aruba 7010 (JP) FIPS/TAA 16p 150W PoE+ 10/100/1000BASE-T 1GBASE-X SFP 32 AP and 2K Clnts Cntrlr	JW705A
	Step 2: Select AC power cord	
	PC-AC-ARG AC power cord 250V/10A 1.8m C13 to IRAM 2073	JW113A
	PC-AC-AUS AC power cord 250V/10A 1.8m C13 to AS3112	JW114A
	PC-AC-BR AC power cord 250V/10A 1.8m C13 to NBR 14136	JW115A
	PC-AC-CHN AC power cord 250V/10A 1.8m C13 to GB2099	JW116A
	PC-AC-DEN AC power cord 250V/10A 1.8m C13 to AFSNIT 107-2-D1	JW117A
	PC-AC-EC AC power cord 250V/10A 1.8m C13 to CEE7/7	JW118A
	PC-AC-IN AC power cord 250V/6A 1.8m C13 to IS1293	JW119A
	PC-AC-IL AC power cord 250V/10A 1.8m C13 to SI32	JW120A
	PC-AC-IT AC power cord 250V/10A 1.8m C13 to CEI 23-50	JW121A
	PC-AC-JPN AC power cord 125V/12A 1.8m C13 to JISC 8303	JW122A
	PC-AC-KOR AC power cord 250V/7A 1.8m C13 to KSC 8305	JW123A
	PC-AC-NA AC power cord 125V/10A 1.8m C13 to NEMA 5-15P	JW124A
	PC-AC-SWI AC power cord 220V/10A 1.8m C13 to SEV 1011	JW125A
	PC-AC-UK AC power cord 250V/10A 1.8m C13 to BS1363	JW127A
	PC-AC-ZA AC power cord 250V/10A 1.8m C13 to SANS 164-1	JW128A
	Step 3: Select Transceivers for SFP Ports	
	SFP-LX 1000BASE-LX SFP 1310nm LC Connector Pluggable GbE XCVR	JW087A
	SFP-SX 1000BASE-SX SFP 850nm LC Connector Pluggable GbE XCVR	JW088A
	Notes: There are 2 SFP 10/100/1000 ports on 7010	
	Step 4: Spare Mount Kit	
	Aruba 7010-MNT-19 7010 Series Replacement 19-inch Rack Mounting Kit	JW085A



Configuration Information

7024 Ordering Guide

Remarks	Description	SKU
	Step 1: Select the appropriate 7024 Chassis	
	Aruba 7024 (RW) 24-port 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW682A
	Aruba 7024 (US) 24-port 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW683A
	Aruba 7024 (IL) 24-port 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW684A
	Aruba 7024 (JP) 24-port 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW685A
	Aruba 7024 (RW) FIPS/TAA-compliant 24p 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW706A
	Aruba 7024 (US) FIPS/TAA-compliant 24p 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW707A
	Aruba 7024 (IL) FIPS/TAA-compliant 24p 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW708A
	Aruba 7024 (JP) FIPS/TAA-compliant 24p 400W PoE+ 10G BASE-X SFP+ 32 AP and 2K Clients Controller	JW709A
	Step 2: Select AC power cord	
	PC-AC-ARG AC power cord 250V/10A 1.8m C13 to IRAM 2073	JW113A
	PC-AC-AUS AC power cord 250V/10A 1.8m C13 to AS3112	JW114A
	PC-AC-BR AC power cord 250V/10A 1.8m C13 to NBR 14136	JW115A
	PC-AC-CHN AC power cord 250V/10A 1.8m C13 to GB2099	JW116A
	PC-AC-DEN AC power cord 250V/10A 1.8m C13 to AFSNIT 107-2-D1	JW117A
	PC-AC-EC AC power cord 250V/10A 1.8m C13 to CEE7/7	JW118A
	PC-AC-IN AC power cord 250V/6A 1.8m C13 to IS1293	JW119A
	PC-AC-IL AC power cord 250V/10A 1.8m C13 to SI32	JW120A
	PC-AC-IT AC power cord 250V/10A 1.8m C13 to CEI 23-50	JW121A
	PC-AC-JPN AC power cord 125V/12A 1.8m C13 to JISC 8303	JW122A
	PC-AC-KOR AC power cord 250V/7A 1.8m C13 to KSC 8305	JW123A
	PC-AC-NA AC power cord 125V/10A 1.8m C13 to NEMA 5-15P	JW124A
	PC-AC-SWI AC power cord 220V/10A 1.8m C13 to SEV 1011	JW125A
	PC-AC-UK AC power cord 250V/10A 1.8m C13 to BS1363	JW127A
	PC-AC-ZA AC power cord 250V/10A 1.8m C13 to SANS 164-1	JW128A
	Step 3: Select Transceivers for SFP/SFP+ Ports (Optional)	
	SFP-LX 1000BASE-LX SFP 1310nm LC Connector Pluggable GbE XCVR	JW087A
	SFP-SX 1000BASE-SX SFP 850nm LC Connector Pluggable GbE XCVR	JW088A
	SFP-TX 1000BASE-T SFP Copper GbE RJ45 Connector Pluggable XCVR	JW089A
	SFP-10GE-LRM 10GBASE-LRM SFP+ 1310nm LC Connector Pluggable 10GbE XCVR	JW090A
	SFP-10GE-SR 10GBASE-SR SFP+ 850nm Pluggable LC Connector 10GbE XCVR	JW091A
	SFP-10GE-LR 10GBASE-LR SFP+ 1310nm Pluggable LC Connector 10GbE XCVR	JW092A
	DAC-SFP-10GE-1M 1m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW101A
	DAC-SFP-10GE-3M 3m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW102A
	DAC-SFP-10GE-50CM 50cm 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW100A
	DAC-SFP-10GE-5M 5m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW103A
	DAC-SFP-10GE-7M 7m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW104A
	Step 4: Mount (Optional)	
	Aruba 7030-MNT-19 7030 Series Replacement 19-inch Rack Mounting Kit	JW086A
	Aruba SPR-WL2-MNT S1500-24/-48/S2500/S1500-24/-48/S2500 Wall and Rack Mount Kit	JW083A

Configuration Information

7030 Ordering Guide

Remarks	Description	SKU
	Step 1: Select the appropriate 7030 Chassis	
	Aruba 7030 (RW) 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clients Controller	JW686A
	Aruba 7030 (US) 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clients Controller	JW687A
	Aruba 7030 (IL) 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clients Controller	JW688A
	Aruba 7030 (JP) 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clients Controller	JW689A
	Aruba 7030 (EG) 8x 1000BASE-T or 8xSFP64 AP Branch Controller	JY851A
	Aruba 7030 (RW) FIPS/TAA 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clnts Cntrlr	JW710A
	Aruba 7030 (US) FIPS/TAA 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clnts Cntrlr	JW711A
	Aruba 7030 (IL) FIPS/TAA 8p Dual Pers 10/100/1000BASE-T 1GBASE-X SFP 64 AP and 4K Clnts Cntrlr	JW712A
	Aruba 7030 (JP) FIPS/TAA 8p Dual Pers 10/100/1000BASE-T/1GBASE-X SFP 64 AP and 4K Clnts Cntrlr	JW713A
	Step 2: Select AC power cord for main power supply for AC Powered Units	
	PC-AC-ARG AC power cord 250V/10A 1.8m C13 to IRAM 2073	JW113A
	PC-AC-AUS AC power cord 250V/10A 1.8m C13 to AS3112	JW114A
	PC-AC-BR AC power cord 250V/10A 1.8m C13 to NBR 14136	JW115A
	PC-AC-CHN AC power cord 250V/10A 1.8m C13 to GB2099	JW116A
	PC-AC-DEN AC power cord 250V/10A 1.8m C13 to AFSNIT 107-2-D1	JW117A
	PC-AC-EC AC power cord 250V/10A 1.8m C13 to CEE7/7	JW118A
	PC-AC-IN AC power cord 250V/6A 1.8m C13 to IS1293	JW119A
	PC-AC-IL AC power cord 250V/10A 1.8m C13 to SI32	JW120A
	PC-AC-IT AC power cord 250V/10A 1.8m C13 to CEI 23-50	JW121A
	PC-AC-JPN AC power cord 125V/12A 1.8m C13 to JISC 8303	JW122A
	PC-AC-KOR AC power cord 250V/7A 1.8m C13 to KSC 8305	JW123A
	PC-AC-NA AC power cord 125V/10A 1.8m C13 to NEMA 5-15P	JW124A
	PC-AC-SWI AC power cord 220V/10A 1.8m C13 to SEV 1011	JW125A
	PC-AC-UK AC power cord 250V/10A 1.8m C13 to BS1363	JW127A
	PC-AC-ZA AC power cord 250V/10A 1.8m C13 to SANS 164-1	JW128A
	Step 3: Select Transceivers for Combo Ports (Optional)	
	SFP-LX 1000BASE-LX SFP 1310nm LC Connector Pluggable GbE XCVR	JW087A
	SFP-SX 1000BASE-SX SFP 850nm LC Connector Pluggable GbE XCVR	JW088A
Notes:	There are 8 combo ports on 7030 10/100/1000 or SFP	
	Step 4: Mount (Optional)	
	Aruba 7030-MNT-19 7030 Series Replacement 19-inch Rack Mounting Kit	JW086A



Related Options

Transceivers				
7010	7024	7030	Description	SKU
X	X	X	SFP-LX 1000BASE-LX SFP 1310nm LC Connector Pluggable GbE XCVR	JW087A
X	X	X	SFP-SX 1000BASE-SX SFP 850nm LC Connector Pluggable GbE XCVR	JW088A
X	X	X	SFP-TX 1000BASE-T SFP Copper GbE RJ45 Connector Pluggable XCVR	JW089A
X	X	X	Aruba SFP-EX 1000BASE-EX SFP 1310nm LC Connector Pluggable GbE XCVR	JW149A
X	X	X	Aruba SFP-ZX 1000BASE-ZX SFP 1310nm LC Connector Pluggable GbE XCVR	JW150A
X ¹	X ¹	X ¹	Aruba 1G SFP LC LX 10km SMF Transceiver	J4859D
X ¹	X ¹	X ¹	Aruba 1G SFP LC SX 500m OM2 MMF Transceiver	J4858D
X ²	X ²	X ²	Aruba 1G SFP LC LH 70km SMF Transceiver	J4860D
X ¹	X ¹	X ¹	Aruba 1G SFP RJ45 T 100m Cat5e Transceiver	J8177D
	X		SFP-10GE-LR 10GBASE-LR SFP+ 1310nm Pluggable LC Connector 10GbE XCVR	JW092A
	X		SFP-10GE-SR 10GBASE-SR SFP+ 850nm Pluggable LC Connector 10GbE XCVR	JW091A
	X		SFP-10GE-LRM 10GBASE-LRM SFP+ 1310nm LC Connector Pluggable 10GbE XCVR	JW090A
	X		DAC-SFP-10GE-50CM 50cm 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW100A
	X		DAC-SFP-10GE-1M 1m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW101A
	X		DAC-SFP-10GE-3M 3m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW102A
	X		DAC-SFP-10GE-5M 5m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW103A
	X		DAC-SFP-10GE-7M 7m 10GbE SFP+ Twinax Connectors Direct Attach Cable	JW104A
	X		Aruba SFP-10GE-ER 10GBASE-ER SFP+ 1310nm LC Connector Pluggable 10GbE XCVR	JW147A
	X ¹		Aruba 10G SFP+ LC SR 300m OM3 MMF Transceiver	J9150D
	X ¹		Aruba 10G SFP+ LC LR 10km SMF Transceiver	J9151E
	X ¹		Aruba 10G SFP+ LC LRM 220m OM2 MMF Transceiver	J9152D
	X ¹		Aruba 10G SFP+ LC ER 40km SMF Transceiver	J9153D
	X ¹		Aruba 10G SFP+ to SFP+ 1m Direct Attach Copper Cable	J9281D
	X ¹		Aruba 10G SFP+ to SFP+ 3m Direct Attach Copper Cable	J9283D
	X ¹		Aruba 10G SFP+ to SFP+ 7m Direct Attach Copper Cable	J9285D

Notes:

- ¹ Default minimum ArubaOS software version is 6.5.3.0 and 8.1.0.0
- ² Minimum ArubaOS software version is 6.5.4.7 and 8.4.0.0

For additional information on the Aruba 7000 Series Mobility Controllers please refer to:

- ArubaOS Network Operating System Data Sheet (and licenses)
- https://www.arubanetworks.com/assets/ds/DS_AOS.pdf
- 7000 Series Mobility Controller – <https://www.arubanetworks.com/products/networking/controllers/7000-series/>
- 7000 Series Ordering Guide – https://www.arubanetworks.com/assets/og/OG_7000Series.pdf



Related Options

SD-WAN Cloud Subscription Licenses

Remarks	Description	SKU
	Aruba 70xx or 90xx Gateway Foundation 1yr Subscription E-STU	JZ118AAE
	Aruba 70xx or 90xx Gateway Foundation 3yr Subscription E-STU	JZ119AAE
	Aruba 70xx or 90xx Gateway Foundation 5yr Subscription E-STU	JZ120AAE
	Aruba 70xx or 90xx Gateway Foundation 7yr Subscription E-STU	ROG52AAE
	Aruba 70xx or 90xx Gateway Foundation 10yr Subscription E-STU	ROG53AAE
	Aruba 70xx or 90xx Gateway Foundation Base Capacity 1yr Subscription E-STU	JZ124AAE
	Aruba 70xx or 90xx Gateway Foundation Base Capacity 3yr Subscription E-STU	JZ125AAE
	Aruba 70xx or 90xx Gateway Foundation Base Capacity 5yr Subscription E-STU	JZ126AAE
	Aruba 70xx or 90xx Gateway Foundation Base Capacity 7yr Subscription E-STU	ROG56AAE
	Aruba 70xx or 90xx Gateway Foundation Base Capacity 10yr Subscription E-STU	ROG57AAE
	Aruba 70xx or 90xx Gateway Advanced 1yr Subscription E-STU	JZ121AAE
	Aruba 70xx or 90xx Gateway Advanced 3yr Subscription E-STU	JZ122AAE
	Aruba 70xx or 90xx Gateway Advanced 5yr Subscription E-STU	JZ123AAE
	Aruba 70xx or 90xx Gateway Advanced 7yr Subscription E-STU	ROG54AAE
	Aruba 70xx or 90xx Gateway Advanced 10yr Subscription E-STU	ROG55AAE

Mobility Controller Licenses

	Aruba LIC-ENT Enterprise (LIC-AP LIC-PEF LIC-RFP and LIC-AW) Licence Bundle E-LTU	JW471AAE
	Aruba LIC-AP Controller per AP Capacity License E-LTU	JW472AAE
	Aruba LIC-PEF Controller Policy Enforcement Firewall Per AP License E-LTU	JW473AAE
	Aruba LIC-RFP Controller RFProtect Per AP License E-LTU	JW474AAE
	Aruba LIC-ACR Controller Advanced Cryptography 1 Session License E-LTU	Q9B90AAE
	Aruba Controller Web Content Classification 1 Year Subscription E-STU	JY028AAE
	Aruba Controller Web Content Classification 3 Year Subscription E-STU	JY029AAE
	Aruba Controller Web Content Classification 5 Year Subscription E-STU	JY030AAE
	Aruba Controller Web Content Classification 7 Year Subscription E-STU	JY031AAE
	Aruba Controller Web Content Classification 10 Year Subscription E-STU	JY032AAE
	Aruba LIC-ACR Controller Advanced Cryptography 1 Session License E-LTU	Q9B90AAE
	Aruba LIC-7010-PEFV Controller Policy Enforcement Firewall for Aruba 7010 Cntrlr License E-LTU	JW496AAE
	Aruba LIC-7008-PEFV Controller Policy Enforcement Firewall for Aruba 7008 Cntrlr License E-LTU	JY342AAE
	Aruba LIC-7010-PEFV Controller Policy Enforcement Firewall for Aruba 7010 Cntrlr License E-LTU	JW496AAE
	Aruba LIC-7024-PEFV Controller Policy Enforcement Firewall for Aruba 7024 Cntrlr License E-LTU	JW497AAE
	Aruba LIC-7030-PEFV Controller Policy Enforcement Firewall for Aruba 7030 Cntrlr License E-LTU	JW498AAE
	Aruba LIC-VIA Per VIA Client Controller VPN License E-LTU	JZ148AAE

- Notes:**
- For each AP attached to the controller the minimal configuration is 1xLIC-AP per AP. LIC-ENT (JW471AAE) is equivalent to 1 each of LIC-AP, LIC-REF, LIC-RFP, and LIC-AW.
 - LIC-AW is a device license for AirWave Management system
 - The PEFV enables firewall services on a per controller basis for VPN termination such as Aruba VIA, Aruba RAPs and IAP-VPN.
 - PEFV license can also be used for VIA VPN termination. But PEFV is tied to a particular controller and the license capacity scales to the controller user capacity. On the other hand, LIC-VIA license is per VIA user license and is not tied to any particular controller. It can be transferred from one controller to another. Unlike PEFV, LICVIA supports centralized licensing and can be managed by Mobility Master or a Master Controller in AOS 8.x deployment.



Technical Specifications

Performance and Capacity					
Features	7005	7008	7010	7024	7030
Maximum campus or remote AP licenses	16	16	32	32	64
Maximum concurrent users/devices	1,024	1,024	2,048	2,048	4,096
Maximum VLANs	4,096	4,096	4,096	4,096	4,096
Active firewall sessions	16K	16K	32K	32K	64K
Concurrent GRE tunnels	256	256	512	512	1,024
Concurrent IPsec sessions	1,024	1,024	2,048	2,048	4,096
Concurrent tunneled ports	1,024	1,024	2,048	2,048	4,096
Firewall throughput	4 Gbps	4 Gbps	8 Gbps	8 Gbps	8 Gbps
Wired bridged throughput	4 Gbps	4 Gbps	8 Gbps	8 Gbps	8 Gbps
Encrypted throughput 3DES	1.2 Gbps	1.2 Gbps	2.4 Gbps	2.4 Gbps	2.4 Gbps
Encrypted throughput AES-CBC-256	1.3 Gbps	1.3 Gbps	2.6 Gbps	2.6 Gbps	2.6 Gbps
Encrypted throughput AES-CCM	2.0 Gbps	2.0 Gbps	3.4 Gbps	3.4 Gbps	4.0 Gbps
Encrypted throughput AES-GCM-256	1.7 Gbps	1.7 Gbps	3.3 Gbps	3.3 Gbps	3.4 Gbps

Interfaces and Indicators					
Features	7005	7008	7010	7024	7030
Form factor/footprint	Desktop/ fanless	Desktop/ fanless	1 RU	1 RU	1 RU
10/100/1000BASE-T	4	8	16	24	8 (combo)
1000BASE-X	N/A	N/A	2 SFP	N/A	8 (combo)
10G Ports (10G or 1G supported)	N/A	N/A	N/A	2xSFP+	N/A
USB 2.0	1	1	1	1	1
Management/status LEDs	Yes	Yes	Yes	Yes	Yes
LINK/ACT and status LEDs	Yes	Yes	Yes	Yes	Yes
LCD panel and navigation buttons	No	No	Yes	Yes	Yes
Console port	Mini USB/RJ-45	RJ-45	Mini USB/RJ-45	micro USB/RJ-45	Mini USB/RJ-45
Out-of-band management port	No	No	Yes	Yes	Yes

Technical Specifications

Power Over Ethernet (PoE) Support

Features	7005	7008	7010	7024	7030
PoE ¹ Role/Model	Powered Device (PD)	Power Source Equipment (PSE)	PSE	PSE	-
PoE In or Out	In – Port 0	Out	Out	Out	-
Number of PoE+ ² capable Ports	-	8	12	24	-
Max concurrent of PoE Ports	-	8	12	24	-
Max concurrent PoE+ Ports	-	3	5	13	-
PoE Power Budget	-	100W	150W	400W	-

Notes:

- ¹ PoE: 802.3af, 15.4W from the PSE and 12.95W at the PD
- ² PoE+: 802.3at, 30W from the PSE and 25.5W at the PD

Physical

Features	7005	7008	7010	7024	7030
Dimensions (H x W x D)	4.1 cm x 20 cm x 20 cm (1.6" x 7.9" x 7.9")	4.2 cm x 20.32 cm x 20.32cm (1.65" x 8.0" x 8.0")	4.42 cm x 31.75 cm x 33.7 cm (1.74" x 12.75" x 13.3")	4.37 cm x 44.2 cm x 31.3 cm (1.72" x 17.4" x 12.32")	4.4 cm x 30.5 cm x 21.1 cm (1.7" x 12" x 8.3")
Weight	0.92 kg (2.03 lbs)	1.0 kg (2.2 lbs)	3.4 kg (7.5 lbs)	5.127 kg (11.3 lbs)	2.06 kg (4.54 lbs)
MTBF (hours, @ 25C)	323,896	300,000	232,843	311,901	390,679

Environmental Range

Specification	7005	7008	7010	7024	7030
Operating temperature	0° C to 40° C				
Storage temperature	-40° C to 70° C				
Humidity/storage humidity	5% to 95%, NC	5% to 95%, NC	5% to 95%, NC	10% to 95%, NC	5% to 95%, NC
Operating altitude	10,000 feet				
Acoustic noise ¹	0 dBA (fanless)	0 dBA (fanless)	39.8 – 58.6 dBA	34.3 – 71.2 dBA	29.1 – 57.4 dBA
Maximum power consumption	16.6 W (with USB)	126W with PoE (26W without PoE)	190 W (with PoE)	450 W (with PoE)	55 W
Power Source	PoE or 12v - 30W	150-watt power supply	internal power supply	internal power supply	internal power supply

Technical Specifications

Power Adapter and Supply Specifications		
Features	12v – 30W	150-watt
Input voltage range	90 VAC to 264 VAC	90 VAC to 264 VAC
Output Voltage	+12VDC, 4A	54VDC, 2.78A
Input frequency	47-63 Hz	47-63 Hz
AC line input current (steady state)	1.0A	2.0A
Operating Temperature	-0o to +40o C	-0o to +40o C
Cooling	-	-
Weight	.24 kg (.53 lbs)	.72 kg (1.58 lbs)

Regulatory and Safety Compliance

Safety certifications

- UL 60950-1 Second Edition
- CAN/CSA-C22.2 No. 60950-1 Second Edition EN 60950-1 Second Edition
- EN 60950:2005
- IEC 60950-1 Second Edition
- NOM (obtained by partners and distributors)

Electromagnetic emissions certifications

- FCC Part 15 Class B CE AS/NZS CISPR22 Class B
- CISPR22 Class A (7010, 7024, 7030), Class B (7005)
- EN55022 Class A (7010, 7024, 7030), Class B (7005)
- ICES-003 Class A (7010, 7024, 7030), Class B (7005)
- VCCI Class A (7010, 7024, 7030), Class B (7005) EN61000-3-2
- EN61000-3-3
- EN 61000-4-2, EN 61000-4-3, EN 61000-4-4, EN 61000-4-5, EN 61000-4-6, EN 61000-4-8, EN 61000-4-11, AS/NZS 3548
- KN22 Class B KCC
- CNS13438 Class B EN55024/CISPR24 KN24
- Industry Canada Class B
- CE mark, cTUVus, CB, C-tick, Anatel, NOM, MIC

Telco

- Common Language Equipment Identifier (CLEI) Code

Regulatory SKU information

- ARCN01014(7005), ARCN0103(7010), ARCN7024(7024), ARCN7030(7030)

Minimum ArubaOS Release

- 7005, AOS 6.4.1.0; 7010, AOS 6.4.1.0; 7024, AOS 6.4.3.0; 7030, AOS 6.4.1.0



Summary of Changes

Date	Version History	Action	Description of Change
05-Oct-2020	Version 7	Changed	Configuration Information section was updated. Obsolete SKUs were removed.
04-Nov-2019	Version 6	Changed	Overview, Standard Features, Configuration Information and Technical Specification sections were updated.
03-Dec-2018	Version 5	Changed	Document name changed to Aruba 7000 Series Mobility Controllers Complete document revised (software feature update)
08-Jan-2018	Version 4	Added	SKUs added: Q9B90AAE, JW538AAE, JW539AAE, JW540AAE, JW541AAE, JW542AAE, JW543AAE, JW544AAE, JY028AAE, JY029AAE, JY030AAE, JY031AAE, JY032AAE
07-Aug-2017	Version 3	Changed	Aruba footer removed. Family series photo updated.
07-Nov-2016	Version 2	Added	Models added: JY849A, JY850A, JY851A
01-Nov-2016	Version 1	New	New QuickSpecs



Copyright

Make the right purchase decision.
Contact our presales specialists.



Chat



Email



Call



Get updates



© Copyright 2020 Hewlett Packard Enterprise Development LP. The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

To learn more, visit: <http://www.hpe.com/networking>

c05272689 - 15702 - Worldwide - V7 - 05-October-2020